



## 5100-W Gas/Propane Generator with Electric Start

- Features a powerful 8 HP, 4-stroke air cooled OHV engine
- This generator can run on gasoline or propane giving you the flexibility to choose
- Equipped with an AVR system and electronic ignition
- Low oil shut-off with indicator light protects the engine
- Keyed electric start and easy start recoil starter
- AC double throw circuit breaker and resets for safe operation
- Neutral bonded to frame
- Fuel Tank Capacity: 15 L
- Weight: 118 lbs.
- Overall Height: 22"
- Overall Width: 22-1/2"
- Overall Depth: 25-1/2"
- Surge Power: 5100 W
- Running Wattage: 4000 W (Gasoline)/3600 W (Propane)
- Engine (OHV): 8 HP
- No Load Speed: 3750 RPM
- Displacement: 224 CC
- Oil Capacity: 0.6 L
- Run Time: 7-8 hrs.
- Noise Level: 75 dB(A)
- Certifications: CSA & EPA Approved
- Includes: (2) 8" Wheels, (1) Pivot Handle, (1) Propane Tank Connection Cable, (1) 12V Battery, (1) Spark Plug Socket, (1) Gasoline/Propane Generator



Model No.	Mfg. No.	Price /Each
UAV629	KCG-5101GE-DF	

## 2000-W Gas Digital Inverter Generators

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Powerful 4.5 HP, 4 stroke air cooled OHV engine
- Designed for quiet operation suitable for home use, camping and boating
- Economical mode switch adjusts the engine speed based on connected load, for improved fuel consumption
- Low oil shut-off, overload and power indicator lights
- AC circuit breaker and reset for safe operation
- Easy start manual recoil starter
- CSA and EPA approved
- Comes with DC cables, spark plug socket, oil fill container, screwdriver and oil drain pipe
- AC Output (Max): 2000 W
- AC Output (Rated): 1600 W
- Amperage: 16.7 A
- DC Output: 12 V/ 8.3 A
- Fuel Tank Capacity: 5.4 L
- Run Time: 5-6 hrs.
- Weight: 58 lbs.



Model No.	Mfg. No.	Price /Each
XC979	KCG-2000I	

## 4500-W Gas Inverter Generator

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Features a powerful 8 HP, 4-stroke air cooled OHV engine, DC USB port, and DC cigarette lighter socket
- Remote start, single-push button electric start or recoil start
- Parallel connectivity between two inverter generators for combined output power
- Fuel Tank Capacity: 12 L
- Weight: 110 lbs.
- Overall Height: 20"
- Overall Width: 16-1/2"
- Overall Depth: 26-1/2"
- Surge Power: 4500 W
- Running Wattage: 3700 W
- AC Outputs: (2) 120V/20 A, (1) 120V/30 A
- DC Output: 12 V
- Engine (OHV): 8 HP
- No Load Speed: 3600 RPM
- Displacement: 224 CC
- Oil Capacity: 0.6 L
- Run Time: 11-12 hrs.
- Noise Level: 64 dB(A)



Model No.	Mfg. No.	Price /Each
UAV630	KCG-4500I	